

BESANTEK Pocket Digital Multimeter which measures AC/DC voltage, DC current, resistance, tests diodes and checking continuity.

Features:

- Hold function.
- Manual ranging.
- Voltage, DC current and resistance measurement.
- Diode and continuity test with buzzer.
- Square wave output.
- Low battery warning indicator.
- LCD display.
- Measurement update speed 2~3 times/second.
- Compact and lightweight.
- Accessories: Instruction manual, battery, test leads and holster.



BST-MT71

Technical Specification:

BST-MT71	
DC Voltage	Range: 200mV/2000mV/20V/200V/250V Accuracy: $\pm(0.5\%+2)$
AC Voltage	Range: 200V/250V Accuracy: $\pm(1.2\%+10)$
DC Current	Range: 2000 μ A/20mA/200mA/10A Accuracy: $\pm(1\%+2)$
Resistance	Range: 200 Ω /2000 Ω /20k Ω /200k Ω /20M Ω /200M Ω Accuracy: $\pm(0.8\%+2)$
Input Impedance for DC Voltage Measurement	10M Ω
Display Count	1999
Measurement Speed	Updates 2~3 times/second
LCD Size	48 x 16 mm
Operating Temperature	0°C~40°C (32°F~104°F)
Operating Humidity	75%RH at 0°C~30°C, 50%RH at 31°C~40°C
Storage Temperature	-10°C~50°C (14°F~122°F)
Power Source	9V battery x 1
Dimensions	130 x 73.5 x 35 mm
Weight	Approx. 156g (battery included)

Accessories

Instruction Manual



Holster



Test Leads



Battery

Ordering Information:

- BST-MT71: Pocket Digital Multimeter.

Safety Standard:

- EN 61326-1:2013,
- EN 61326-2-2:2013,
- UL 61010-1:2012 (3rd),
- UL 61010-2-030:2012,
- UL 61010-2-033:2014

