

## RocketStor 6661A-2USB1

# Thunderbolt™ 3 to 2x 5Gb/s USB 3.2 Adapter

- Thunderbolt™ 3 to 2x 5Gb/s USB 3.2 Ports
- Up to 5Gb/s per-port
- Dual-Port Solution: 2x Type-A Ports
- Supports up to 2x USB 3.2/3.1/3.0/2.0 devices
- Works with any Thunderbolt<sup>™</sup> 3 capable
   Mac or PC platform



### **Dual Type-A Connectors**

The RocketStor 6661A-2USB1 is a versatile USB 3.2 5G connectivity expansion solution for Thunderbolt™ 3 capable host platforms. Each RocketStor 6661A-2USB1 provides dual Type-A ports for maximum compatibility and ease of use. Though optimized for external USB storage devices such as enclosures, USB drives and docks, the RocketStor 6661A-2USB1 is also capable of supporting any industry standard USB 3.2/3.1/3.0/2.0 device or peripheral.

## Works with any Thunderbolt™ 3 capable Mac or PC

Like all HighPoint Thunderbolt<sup>™</sup> 3 I/O Solutions, the RocketStor 6661A-2USB1 was designed with simplicity and ease of use in mind. The unit is shipped preassembled, and ready to use right out of the box. Simply connect the RocketStor to your Thunderbolt<sup>™</sup> Mac or PC using the included Thunderbolt<sup>™</sup> 3 40Gb/s cable, plugin the power adapter, and you are ready to go!

## **Optional Device Cables for any USB Connector Type**

The RocketStor 6661A-2USB1 is capable of supporting nearly any industry-standard USB port type when used in conjunction with the HighPoint USB-C31-1MA (Type-A to Type-C) and USB-A31-06B (Type-A to Micro-B) USB device cables. HighPoint device cables are manufactured to our high-standards of quality, and thoroughly tested to ensure secure connectivity, maximized transfer performance, and years of trouble-free utility.









Feature Specifications	
Host Ports	Thunderbolt™ 3 to 2x USB 3.2 5G
I/O Ports	2x Thunderbolt™ 3 Ports, 2x 5Gb/s USB 3.2 Type-A Ports
Transfer Performance	Up to 5Gb/s Per USB 3.2 Port
Number of Devices	2x USB 3.2/3.1/3.0/2.0 devices or peripherals
Thunderbolt™ Specifications (RS6661A)	<ul> <li>Power delivery: 15W to bus-powered devices</li> <li>Backwards compatible with Thunderbolt™ 2 devices (via Daisy Chain)</li> <li>Supports Daisy-Chain configurations of up to 6 Thunderbolt™ Devices Thunderbolt™ 3 Type-C ports can support USB devices via a USB-C cable (up to USB 3.2 10Gb/s speeds). Note: attaching a USB or display device will end a Daisy Chain configuration.</li> </ul>
System Requirements	
PC Platform	<ul> <li>Computer with a USB-C (Thunderbolt™ 3)</li> <li>Computer with a Thunderbolt 2 port (via Thunderbolt™ 3 to Thunderbolt™ 2 Adapter)</li> </ul>
Windows	Windows 11, 10, 8 / Windows Server 2022, 2019, 2016
Linux	Linux kernel v2.6.31 and later
Mac Platforms	<ul> <li>Mac platform with a Thunderbolt™ 3 or Thunderbolt™ 2 port (via Thunderbolt™ 3 to Thunderbolt™ 2 Adapter)</li> <li>Supports 2012 and later Mac Pro systems; 5.1, 7.1 (Intel Platform compatible)</li> </ul>
macOS	macOS 10.12.6~macOS Monterey 12.x
Hardware Specifications	
Power Supply	External 60W Power Supply
	AC Input: 100–240V, 50-60Hz
Cooling	Dual, Ultra Quiet, high-efficiency Cooling fans
Dimensions	2.25" (W) x 6.42" (H) x 10.12" (D)
Weight	6.0 lbs.
Warranty	1 Year
Compliance Certification	CE, FCC, RoHS, REACH, WEEE, Thunderbolt™
Kit Contents	Integrated 2-Port 10Gb/s USB 3.2 Controller
	RocketStor 6661A Expansion Chassis
	1x 40Gb/s Thunderbolt™ 3 cable
	1x External Power Supply
	1x Power Cord
	Quick Installation Guide
Optional Accessories	
Thunderbolt 3 <sup>™</sup> Cables: <u>TB3-040G-505</u> - 0.5M, 40Gb/s cable <u>TB3-040G-510</u> - 1M, 40Gb/s cable <u>TB3-040G-520</u> - 2M, 40Gb/s cable	USB 3.1 Cables: <u>USB-A31-1MC</u> – 1M, USB-A to USB-C cable <u>USB-A31-2MC</u> – 2M, USB-A to USB-C cable <u>USB-A31-06B</u> – 1M, USB-A to Micro-B cable

#### HighPoint Headquarters

Phone 1-408-942-5800 Fax 1-408-942-5801 E-mail sales@highpoint-tech.com Website www.highpoint-tech.com Address 41650 Christy St. Fremont CA, 94538

#### HighPoint China

Phone + 86(10)-53519056 (Ext. 8003) Fax + 86-10-6897-5074 E-mail sales@highpoint-tech.com Website www.highpoint-tech.cn Address ROOM 512, Building 1, No 4 JinHang Xi Rd, ShunYi District Beijing, 101318, China









